




## Model ZTSCT Closed Transition Transfer Switches Supplement to ZTS Series Product Bulletin



An automatic transfer switch is the single vital link between utility and alternate power supplies. Yet it is the very operation and testing and retransfer back to normal that may be a cause of concern for many users. Loads such as electronic equipment, HID lighting, motor starters, etc., are sensitive to even the 30-100 millisecond outage experienced during a typical transfer switch operation. Therefore, testing and use of the standby system is not optimized and necessary system checks are not performed because of concerns about the effects of transfer.

In addition to these applications, opportunities for peak shaving and utility incentive rates may be passed over because of the inability to accept the short power interruptions inflicted during operation. In response to the needs of these installations, GE Zenith offers the ZTSCT Closed Transition Transfer Switch and ZBTSCT Closed Transition Transfer/Bypass Switch.

These products utilize the proven switching technology of the ZTS/ZTSD Model of transfer switches combined with controls developed during GE Zenith's years of experience in the manufacture of synchronizing switchgear. They provide the capability to transfer in a closed transition mode when both sources are within preset parameters. Utilizing GE Zenith's high speed drive system, the overlap of the normal and alternate sources is less than 100 milliseconds. When one source is not within specified limits, such as during a power failure, the ZTSCT operates in an open transition mode.



### Specification Assistance

GE Zenith offers a complete range of product guide specifications to help you determine your needs.

For more information, please consult your local GE Zenith representative, our factory or our website at [www.geindustrial.com](http://www.geindustrial.com).

### Description and Operation

Closed transition switches have two basic modes of operation. During a failure of one source or an out of specification condition, the ZTSCT Model operates as a standard delayed transition switch (ZTSD Model). This sequence allows clear separation of an unreliable source from an available one.

Closed transition operation takes place when both sources are within preset voltage and frequency parameters and the phase angle differential is less than five degrees. The closed transition sequence may be initiated by the test switch, a load exerciser clock, peak shaving controls or special utility incentive rate signals.

### Application Information:

- Closed transition switches require a momentary (less than 100 ms) paralleling of the standby source with the utility. This usually requires the owner to obtain approval of the installation by the utility.
- The purpose of a closed transition switch is to prevent the momentary outages that occur during transfer of a standard unit. This technology is not normally a substitute for a UPS system as it does not provide stored energy capability but rather acts in a complementary fashion.
- *System application requirements:*  
The generator set must be provided with an isochronous governor stable at a frequency differential of not more than +/- .25% from 60 Hz.

A 24VDC shunt trip circuit is strongly suggested on one of the feeder breakers, normally the generator feeder. Power for this trip circuit and alarm system backup must be supplied from the engine starting batteries or an equivalent source.

# Model ZTSCT

## Specifications / Power Connection Terminals

### Electrical Ratings

- Ratings 100 to 4000 amperes
- 2, 3 or 4 Poles
- Open type, NEMA 1, 3R, 4, 4X and 12
- Available in Transfer Switch (ZTSCT) or Transfer/Bypass Switch (ZBTSCT) styles
- Suitable for emergency and standby applications on all classes of load, 100% tungsten rated through 400 amps
- UL 1008 listed at 480 VAC
- CSA certified at 600 VAC
- IEC listed at 480 VAC

### Performance Features

- Incorporates the applicable features of the ZTS and ZBTS Series
- Source parallel time of less than 100 milliseconds
- Closed transition operation (no power interruption) during transfer and retransfer when sources are within specified parameters
- Open transition transfer operation is initiated upon a source failure
- Available in ZTSCT (utility-generator), ZTSCTU (utility-utility) and ZTSCTM (manual) configurations

### Design and

#### Construction Features

- Electrically operated, mechanically held
- Segmented silver tungsten alloy contacts with separate arcing contacts on all sizes
- Arc quenching grids, enclosed arc chambers, and wide contact air gap
- Components accessible for inspection and maintenance without removal of the switch or the power conductors
- Standard annunciation and operational selection package for user interface
- Active control of the generator governor not required, but is available as an option

Model ZTSCT Transfer Switches								
Ampere Rating	Poles	NEMA 1 Enclosed				Weight		Application Notes
		Height (A)	Width (B)	Depth (C)	Reference Figure	Open Type	NEMA 1	
100, 150	2, 3	66 (128)	24 (61)	19.75 (50)	B	235 (75)	500 (227)	1 – 8
225, 260		74 (188)	30 (76)	19.75 (50)	B	255 (84)	520 (236)	
800, 1000	2, 3	74 (188)	30 (76)	19.75 (50)	B	260 (118)	525 (238)	1 – 8
1200		74 (188)	40 (102)	19.75 (50)	B	280 (127)	610 (277)	
1600	3	90 (229)	30 (76)	48 (122)	C	415 (188)	1140 (517)	1 – 8
2000		90 (229)	36 (91)	48 (122)	C	520 (236)	1305 (592)	
3000	3	90 (229)	30 (76)	48 (122)	C	535 (243)	1260 (572)	1 – 8, 10, 11
	4	90 (229)	36 (91)	48 (122)	C	740 (336)	1465 (665)	
4000	3	90 (229)	40 (102)	60 (152)	C	840 (381)	1665 (755)	1 – 11
	4	90 (229)	46.5 (118)	60 (152)	C	1095 (497)	1920 (871)	

#### Application Notes:

1. Metric dimensions (cm) and weights (Kg) shown in parenthesis adjacent to English measurements in inches and pounds.
2. Includes 1.25" door projection beyond base depth. Allow a minimum of 3" additional depth for projection of handle, light, switches, pushbuttons, etc.
3. All dimensions and weights are approximate and subject to change without notice.
4. Special enclosures (NEMA 3R, 4, 12, etc.) dimensions and layout may differ. Consult the GE Zenith factory for details.
5. Normal and emergency may be ordered inverted on any switch. The load may be inverted 600-1200 amps. Consult the factory for details.
6. Special lug arrangements may require different enclosure dimensions. For certified drawings, contact the GE Zenith factory.
7. Packing materials must be added to weights shown. Allow 15% additional weight for cartons, skids, crates, etc.
8. Add 4" in height for removable lifting lugs.
9. 4000 amp depth dimension shown is standard. Depending on your cable/conduit requirements you may desire a deeper enclosure. Consult the GE Zenith factory for further details.
10. Lug adapters for 3000-4000 amp limits may be staggered length for ease of entrance. Consult the GE Zenith factory for details.
11. Ventilation louvers on both sides of enclosure at 3000 and 4000 amps. One must be clear for airflow with standard cable connections.




Figure B




Figure C

AL-CU UL Listed Solderless Screw-Type Terminals for External Power Connections					
Switch Size Amps	Normal, Emergency, & Load Terminals		Switch Size Amps	Normal Emergency, & Load Terminals	
	Cables/Pole	Wire Ranges		Cables/Pole	Wire Ranges
100-150	1	#8 to 3/0 AWG	800/1000 /1200	4	#2 AWG to 600 MCM
225	1	#4 AWG to 600 MCM	1600	*	
260	1	#4 AWG to 600 MCM	2000		
400	1	#4 AWG to 600 MCM	3000		
600	2	#2 AWG to 600MCM	4000		

#### Notes:

- \* Line and load terminals are located in rear and arranged for bus bar connection. Terminal lugs are available at additional cost. Contact factory for more details.
1. Special terminal lugs and neutral bars are available at additional cost. Contact factory and advise cable sizes and number of conductors per pole.
  2. Fully rated solid neutral (3x standard normal power connection) provided when required by system voltage.
  3. Normal and emergency may be ordered inverted on any switch. Load may be inverted 600-1200 amps. Consult the factory for details.
  4. Lug adapters for 3000-4000 amp units may be staggered length for ease of entrance. Consult the factory for details.
  5. Special lug arrangements may require different enclosure dimensions. For certified drawings, contact the GE Zenith factory.



A Product of GE Industrial Systems  
 General Electric Company  
 830 West 40<sup>th</sup> Street, Chicago, IL 60609 USA  
 773 299-6600, Fax: 630 850-6899  
 www.geindustrial.com

Contents contained in this document are subject to change without notice. Contact GE to verify details.